

HP	VOLTAGE	PHASE	NEC CODE	SF	FULL LOAD AMPS	SF AMPS	LOCKED ROTOR AMPS	RUN KW	START KVA	RUN KVA	MTR. EFFICIENCY @100% FL	PWR. FACT. @SF	PWR. FACT. @100% FL	PWR. FACT. @75% FL	PWR. FACT. @50% FL
15	208				46.4	55.3	353.0	13.7	127.0	16.7	92.4	83.5	81.8	77.3	68.6
	230	K	1.15		42.0	50.0	320.0	13.7	127.3	16.7	92.4	83.5	81.8	77.3	68.6
	460				21.0	25.0	160.0	13.7	127.3	16.7	92.4	83.5	81.8	77.3	68.6
	575	J			16.8	20.0	120.0	13.7	119.4	16.7	92.4	83.5	81.8	77.3	68.6
20	208				58.6	64.6	353.0	18.0	127.0	21.1	93.0	85.8	84.9	81.8	75.0
	230	3	H	1.15	53.0	58.4	320.0	18.0	127.3	21.1	93.0	85.8	84.9	81.8	75.0
	460				26.5	29.2	160.0	18.0	127.3	21.1	93.0	85.8	84.9	81.8	75.0
	575	G			21.2	23.4	120.0	18.0	119.4	21.1	93.0	85.8	84.9	81.8	75.0
	230				58.4	58.4	320.0	20.1	127.3	23.2	93.0	-	85.8	83.5	77.6
23	460	F	1.0		29.2	29.2	160.0	20.1	127.3	23.2	93.0	-	85.8	83.5	77.6
	575				23.4	23.4	120.0	20.1	119.4	23.3	93.0	-	85.8	83.5	77.6